

CONNECTORS USED:

PART DESCRIPTION	PART NAME	MANUFACT.	QTY
PIN HEADER (INPUT SIDE CN1)	B3P5-VH	JST	1
PIN HEADER(OUTPUT SIDE CN51)	B4P-VH	JST	1

*OUTPUT CURRENT OF EACH CONNECTOR PIN MUST BE LESS THAN 5A.

MATCHING HOUSINGS AND PINS(NOT INCLUDED WITH THE PRODUCT):

SOCKET HOUSING (CN1)	VHR-5N	JST	1
SOCKET HOUSING (CN51)	VHR-4N	JST	1
TERMINAL PINS	SVH-21T-P1.1	JST	7

HAND CRIMPING TOOL : YC-160R CN1,CN2(CN51) MANUFACTURER : JST
MATCHING WIRE HARNESS :

* NOT INCLUDED WITH THE PRODUCT,NEED TO PURCHASE SEPARATELY.


PART DESCRIPTION	PART NAME	MANUFACTURER	QTY
INPUT WIRE HARNESS	CA100-33-16	XIAMEN MACRO-S	1
OUTPUT WIRE HARNESS	CA100-33-90A	XIAMEN MACRO-S	1

NOTES

- A: THE 4- ϕ 3.5 HOLE ARE CUSTOMER CHASSIS MOUNTING HOLES. ALL MUST BE SCREWED IN ORDER TO CONFORM THE VIBRATION SPEC.
- B: MODEL NAME, MAXIMUM OUTPUT POWER, NOMINAL OUTPUT VOLTAGE, MAXIMUM OUTPUT CURRENT, ARE SHOWN HERE IN ACCORDANCE WITH THE SPECIFICATIONS.
- C: COUNTRY OF MANUFACTURE WILL BE SHOWN HERE.
- D: \perp IS FOR SAFETY GROUND CONNECTION.
- E: TO KEEP THE DISTANCE MORE THAN 4mm BETWEEN PC-BOARD EDGE AND CUSTOMER'S CHASSIS.

NAME PLATE

SEE NOTE B



SEE NOTE C

(unit : mm)

MODEL NAME	CUS20E
TDK-Lambda	
CA860-02-01	