

CONNECTORS USED:


| PART DESCRIPTION | PART NAME | MANUFACTURER | QTY |
|------------------------------|-----------|--------------|-----|
| PIN HEADER (INPUT SIDE CN1) | B3P-5-VH | J.S.T | 1 |
| PIN HEADER(OUTPUT SIDE CN51) | B4P-VH | J.S.T | 1 |

^{*}OUTPUT CURRENT OF EACH CONNECTOR PIN MUST BE LESS THAN 5A.

MATCHING HOUSINGS & PINS (NOT INCLUDED WITH PRODUCT):

| SOCKET HOUSING (CN1) | VHR-5N | J.S.T | 1 |
|------------------------|--------------|-------|---|
| SOCKET HOUSING (CN51) | VHR-4N | J.S.T | 1 |
| TERMINAL PINS (CN1,51) | SVH-21T-P1.1 | J.S.T | 7 |

HAND CRIMPING TOOL: YC-160R MANUFACTURER: J.S.T.



SCALE FOR NAME PLATE: 2/1

NOTES

- A: 4-Ø3.5 HOLES ARE CUSTOMER'S CHASSIS MOUNTING HOLES. ALL MUST BE SCREWED IN ORDER TO CONFORM THE VIBRATION SPEC.
- B : MODEL NAME, NOMINAL OUTPUT VOLTAGE,
 AVERAGE OUTPUT CURRENT AND PEAK OUTPUT CURRENT
 ARE SHOWN HERE IN ACCORDANCE WITH THE SPECIFICATIONS.
- C : COUNTRY OF MANUFACTURE WILL BE SHOWN HERE.
- SEE NOTE C D : TO KEEP THE DISTANCE MORE THAN 2mm BETWEEN PC-BOARD EDGE AND CUSTOMER'S CHASSIS.
 - E : FG IS FOR SAFETY GROUND CONNECTION.

